
DS135-PR 5" Designer Series Passive Radiator





FEATURES

- Allows tuning small enclosures lower than using conventional ports
- Rear mounted screw allows easy mass adjustment for custom tuning
- Perfect match for Dayton Audio's paper cone Designer Series drivers
- Cosmetic frame edge looks great even when surface mounted

27.7 Hz
3.93
21.8g
1.52 mm/N
75.4 cm ²
60.3 cm ³
12.2 liters
8 mm
1 kg/s

 $\textbf{Note:} \ \mathsf{Parameters} \ \mathsf{above} \ \mathsf{are} \ \mathsf{for} \ \mathsf{the} \ \mathsf{passive} \ \mathsf{only} \ \mathsf{with} \ \mathsf{no} \ \mathsf{additional} \ \mathsf{mass} \ \mathsf{added}.$